



**TECHNICAL DATA** NOTE: DATA MAY VARY BY CONFIGURATION. SEE CONFIGURATION SECTION.

|           |                           |
|-----------|---------------------------|
| Body Type | montaje directo a motores |
| Interface | Eaton/Char-Lynn 2000      |

**CONFIGURATION OPTIONS**

**Model Code Example: YRGULANAL**

| CONTROL  | (L)                       | ADJUSTMENT RANGE  | (A)      | SEAL MATERIAL | (N) |
|----------|---------------------------|---|----------|---------------|-----|
| <b>L</b> | Standard Screw Adjustment | <b>A</b> 500 - 3000 psi (35 - 210 bar), 1000 psi (70 bar) Standard Setting  | <b>N</b> | Buna-N        |     |
|          |                           | <b>B</b> 300 - 1500 psi (20 - 105 bar), 1000 psi (70 bar) Standard Setting  | <b>V</b> | Viton         |     |
|          |                           | <b>C</b> 1000 - 6000 psi (70 - 420 bar), 1000 psi (70 bar) Standard Setting |          |               |     |
|          |                           | <b>D</b> 200 - 800 psi (14 - 55 bar), 400 psi (28 bar) Standard Setting     |          |               |     |
|          |                           | <b>E</b> 100 - 400 psi (7 - 28 bar), 200 psi (14 bar) Standard Setting      |          |               |     |
|          |                           | <b>S</b> 50 - 200 psi (3,5 - 14 bar), 100 psi (7 bar) Standard Setting      |          |               |     |
|          |                           | <b>W</b> 800 - 4500 psi (55 - 315 bar), 1000 psi (70 bar) Standard Setting  |          |               |     |

**PRIMARY CARTRIDGE**

(A)

|          |   |
|----------|---|
| <b>A</b> | A (with RDDA primary cartridge, Acción-directa alivio válvula )               |
| A        | A (with RDDA3 primary cartridge, No-ajustable acción-directa alivio válvula ) |

**INCLUDED COMPONENTS**

| Part         | Description         | Quantity |
|--------------|---------------------|----------|
| 500-001-117* | O-Ring              | 2        |
| DSCHXHN      | Cartridge           | 1        |
| RDDALAN      | Cartridge - Primary | 2        |
| RPECLNN      | Cartridge           | 1        |